

ST4812M08 Power Strip

Product Information

Product Specification

- 48" aluminum case
- 12 outlets, evenly spaced
- 15 amp circuit breaker
- 8ft, 3 prong power cord
- UL and CSA approved
- Mounting clips for wood or metal installation

Installation and Use

- Plug the power cord into a utility outlet. The power strip's power cord should only be connected to a standard 3-wire grounded 120V AC 60 Hz outlet.
- Plug the AC power cords of the equipment into the power strip. Do not overload the power strip. This power strip is rated at 15 amps [1800 watts using 120 volt AC (Watt = Volt x Amp)]. Each individual outlet can handle a load of up to 15 amps, but the total load should not exceed 15 amps, for all outlets combined.
- Turn the power switch on. The switch should light up.

Circuit Breaker

The power switch also functions as a circuit breaker. If the circuit breaker trips, the power switch will jump to the "off" position and outlets will cease to provide power. Reduce the load on the power strip to 15 amps or less before turning the power switch back on. When switching the power strip back on, the circuit breaker is automatically reset.

Surge Protection

The power strip has a built-in surge protection function with indicator. When the indicator light is on, surge protection is active. The surge protection device is capable of withstanding power surges of up to 400 joules. If a large power surge occurs, the protection function and the indicator may shut down and become inactive. However, in most situations, the power strip will still work properly, even without the surge protection function.

Caution

Do not use with extension cords or adapters that have no ground connection. Do not connect to an ungrounded outlet. This power strip is designed for indoor use only. Install the power strip away from heat and moisture.

Limited Warranty

Sima International, Inc. warrants this product against defects in material and workmanship for a period of 90 days, from the date of purchase. During the warranty period, Sima International will repair or replace the product. This warranty does not apply if the product has been damaged by accident, abuse, misuse or misapplication, nor as a result of service or modification made by others. Sima International is not responsible for incidental or consequential damages resulting from the use of this product. This includes damages to intellectual information, property and personal injury. Sima International reserves the right to make changes in future product design, without reservation and without notification to its users.

Return Policy

Please contact the Customer Support Department to obtain a Return Merchandise Authorization (RMA) number, before shipping the product back to Sima International. Returns will not be accepted without a valid RMA number. For faster service, please have the following information on hand when calling for an RMA number: customer name, invoice number and reason for return. Shipping charges on returned items are the customer's responsibility. Products should be returned with shipping charges prepaid, along with proof of purchase, a description of the problem and the issued RMA number.

Sima International, Inc.

Customer Support Department

+1-949-830-3684

service@simaintl.com

- Sima International, Inc. -