

PCI32/64 BUS PINOUT

COMPONENT SIDE B	PIN NO	SOLDER SIDE A
-12V	01	TRST#
TCK	02	+12V
GND	03	TMS
TDO	04	TDI
+5V	05	+5V
+5V	06	INTA#
INTB#	07	INTC#
INTD#	08	+5V
PRSN1#	09	Reserved
Reserved	10	+VIO
PRSN2#	11	Reserved
3.3V KEY / GND	12	3.3V KEY / GND
3.3V KEY / GND	13	3.3V KEY / GND
Reserved	14	3.3Vaux / Reserved
GND	15	RST#
CLK	16	+VIO
GND	17	GNT#
REQ#	18	GND
+VIO	19	PME# / Reserved
AD[31]	20	AD[30]
AD[29]	21	+3.3V
GND	22	AD[28]
AD[27]	23	AD[26]
AD[25]	24	GND
+3.3V	25	AD[24]
C/BE[3]#	26	IDSEL
AD[23]	27	+3.3V
GND	28	AD[22]
AD[21]	29	AD[20]
AD[19]	30	GND
+3.3V	31	AD[18]

PCI32/64 BUS PINOUT

COMPONENT SIDE B	PIN NO	SOLDER SIDE A
AD[17]	32	AD[16]
C/BE[2]#	33	+3.3V
GND	34	FRAME#
IRDY#	35	GND
+3.3V	36	TRDY#
DEVSEL#	37	GND
PCIX / GND	38	STOP#
LOCK#	39	+3.3V
PERR#	40	SMBCLK / Rsvd
+3.3V	41	SMBDAT / Rsvd
SERR#	42	GND
+3.3V	43	PAR
C/BE[1]#	44	AD[15]
AD[14]	45	+3.3V
GND	46	AD[13]
AD[12]	47	AD[11]
AD[10]	48	GND
M66EN / GND	49	AD[09]
GND / 5V KEY	50	GND / 5V KEY
GND / 5V KEY	51	GND / 5V KEY
AD[08]	52	C/BE[0]#
AD[07]	53	+3.3V
+3.3V	54	AD[06]
AD[05]	55	AD[04]
AD[03]	56	GND
GND	57	AD[02]
AD[01]	58	AD[00]
+VIO	59	+VIO
ACK64#	60	REQ64#
+5V	61	+5V
+5V	62	+5V

PCI64 BUS PINOUT

COMPONENT SIDE B	PIN NO	SOLDER SIDE A
64 bit Spacer KEY	-	64 bit Spacer KEY
64 bit Spacer KEY	-	64 bit Spacer KEY
Reserved	63	GND
GND	64	C/BE[7]#
C/BE[6]#	65	C/BE[5]#
C/BE[4]#	66	+VIO
GND	67	PAR64
AD[63]	68	AD[62]
AD[61]	69	GND
+VIO	70	AD[60]
AD[59]	71	AD[58]
AD[57]	72	GND
GND	73	AD[56]
AD[55]	74	AD[54]
AD[53]	75	+VIO
GND	76	AD[52]
AD[51]	77	AD[50]
AD[49]	78	GND
+VIO	79	AD[48]
AD[47]	80	AD[46]
AD[45]	81	GND
GND	82	AD[44]
AD[43]	83	AD[42]
AD[41]	84	+VIO
GND	85	AD[40]
AD[39]	86	AD[38]
AD[37]	87	GND
+VIO	88	AD[36]
AD[35]	89	AD[34]
AD[33]	90	GND
GND	91	AD[32]
Reserved	92	Reserved
Reserved	93	GND
GND	94	Reserved